



RVX-PSU-ALM-16

Power Supply for X-SERIES cameras with 16 alarm inputs-3 alarm outputs

Connectivity to the X-SERIES camera control equipment and alarms via pluggable terminal blocks. 16 alarm inputs can be individually assigned normally open or normally closed via dipswitch. Alarm inputs can activate presets and tours. Alarms can be masked on a timed basis for weekend and weekday operation. 3 alarm 0V relay outputs for ALARM, WASH and AUX.

Key Features

- 16 alarm inputs, 3 alarm outputs
- Connections via pluggable terminal blocks
- IP 67 weatherproof enclosure
- Alarm handling/masking
- Pre-installed cable glands
- On board lightning protection

Specification

Mechanical

Connections	Pluggable terminal blocks and BNC connections
Glands	1 x 20mm Gland, 1 x 16mm Gland, 3 x 12mm Glands

Environmental and physical

Material	ABS
Operating Temperature	-35°C to +50°C
Weatherproof	IP 67 rated enclosure
Dimensions	230 x 140 x 100mm (w x l x h)
Weight	1kg

Power

Input	110Vac to 240Vac
Output	24V 100VA